

SF-ROUTER-4G-CAT6

Safire Router 4G 300Mbps Download
50Mbps Upstream
RJ45 10/100/1000Mbps Ports
Wi-Fi 5 Dual Band AC1200Mbps
(867Mbps+300Mbps)
Up to 64 simultaneous WiFi
connections (32+32)
Battery 7.4V 2000 mAh up to 4h
autonomy
Micro SIM card slot



Router 4G Cat 6 with WiFi
SIM 4G/3G card access (not included)
WiFi access point 802.11 b/g/n/ac dual band and 4 Gigabit Ethernet ports RJ45 10/100/1000
Up to 64 WiFi connections (32+32)
Battery 7.4V 2000 mAh up to 4h of autonomy
Activity indicator LEDs

cctvdi@com

Unit 6A Aran Centre, Blessington Business Park
Blessington, Co. Wicklow, W91 VN27 Ireland


+353 1 4433386 sales@cctvdi.com

www.cctvdi.com

Specifications

LTE	Safire LTE 4G Cat 6 (300Mbps/50Mbps)
LTE bands	4G FDD: B1/25(2)/3/66(4)/26(5)/7/8/12(17)/20/28 4G TDD:B38/B39/40/41(200M) 3G WCDMA: B1/2/4/5/8 2G GSM: B2/3/5/8
WiFi	IEEE 802.11 b/g/n/ac 2.4Ghz + 5GHz Access Point
WiFi Antennas	2 internal of 3 dBi
Ethernet	4 Gigabit LAN ports RJ45 10/100/1000Mbps
SIM	MicroSIM card slot 4G / 3G (not included)
Power	DC 12 V 1 A (including power supply)
Battery	7.4V 2000 mAh up to 4h autonomy (included)
LED	Power, Connection, WiFi, Messaging and Battery Indicators
Download speed	Up to 300 Mbps LTE CAT 6
Upload speed	Up to 50 Mbps LTE CAT 6
LTE Antennas	2 external of 5 dBi 2 internal of 3 dBi
Dimensions	180 x 132 x 48 mm
Weight	290 g (without battery)

cctvdi  **com**

 Unit 6A Aran Centre, Blessington Business Park
Blessington, Co. Wicklow, W91 VN27 Ireland

 +353 1 4433386  sales@cctvdi.com

 www.cctvdi.com